

# COACH 400

## Personal Wireless PA System



### FEATURES

- 40W Class-D amplifier to power a 4" full-range driver.
- MIC IN (Φ6.3mm jack) for microphone with volume control.
- AUX IN (Φ3.5mm jack) with volume control.
- One diversity receiver module with fixed/16 frequencies.(optional).
- Built-in USB music player & recorder with LCD screen and remote control.
- AUX OUT (Φ3.5mm jack) for external audio recording.
- Equalizer for all audio inputs.
- Two alarm sounds for emergency broadcasting.
- Smart charging circuit with battery indicator LED and charging LED.
- Up to 12 hours operating time per charge with lithium battery.
- User friendly battery compartment design for simple battery replacement.
- Tripod stand mountable with ST-30.
- 2 power modes: Internal Rechargeable battery & DC jack.

### SPECIFICATIONS

|                         |   |
|-------------------------|---|
| <b>Model</b>            | COACH 400                                 |
| <b>Max power output</b> | 40W, 4Ω load (class-D)                    |
| <b>Speaker system</b>   | 4" full range                             |
| <b>Audio input</b>      | Mic in, Aux in                            |
| <b>Audio output</b>     | Aux out                                   |
| <b>T.H.D.</b>           | < 0.5%                                    |
| <b>Freq. response</b>   | 50Hz-20KHz ± 3dB                          |
| <b>Antenna</b>          | Built-in                                  |
| <b>Power supply</b>     | 100-240V AC, 18-20V DC/2.5A               |
| <b>Battery type</b>     | Lithium                                   |
| <b>Battery spec</b>     | 14.8V/2.6A                                |
| <b>Battery Q'ty</b>     | 1   |
| <b>Standby time</b>     | 5-6 hours in music, 10-12 hours in speech |
| <b>Charging time</b>    | about 4 hours                             |
| <b>Dimension (mm)</b>   | 156(H) x 156(W) x 205(D)                  |
| <b>Weight (kg)</b>      | 1.6                                       |



\*\* Specifications and design are subject to change without prior notice.